

## Twin Split Digital Inverter

	Aussengerät RAV-	Innengerät RAV-	HP	Leistung	Leistung	Leistungs-	EER	SEER	Energie-
				nominal	min. – max.	aufnahme			
				kW	kW	kW			
4-Wege- Kassettengerät	GM1102AT8W-E	HM561UTP-E	4	9.5	3.0 – 11.2	2.87	3.31	5.94	A+
	GM1402AT8W-E	HM801UTP-E	5	12.0	3.0 – 13.2	4.29	2.80	5.71	A+
	GM1602AT8W-E	HM801UTP-E	6	14.0	3.0 – 16.0	4.43	3.12	6.30	A+
Kompaktes 4-Wege- Kassettengerät	GM1102AT8W-E	HM561MUT-E	4	9.5	3.0 – 11.2	3.00	3.17	5.50	A
Kanalgerät	GM1102AT8W-E	HM561BTP-E	4	9.5	3.0 – 11.2	2.99	3.18	5.28	A
	GM1402AT8W-E	HM801BTP-E	5	12.1	3.0 – 13.2	4.42	2.74	5.36	–
	GM1602AT8W-E	HM801BTP-E	6	14.0	3.0 – 16.0	4.43	3.12	6.30	A+
Flaches Kanalgerät	GM1102AT8W-E	HM561SDT-E	4	9.5	3.0 – 11.2	3.03	3.14	5.32	A
Deckengerät	GM1102AT8W-E	HM561CTP-E	4	9.5	3.0 – 11.2	2.95	3.22	5.86	A+
	GM1402AT8W-E	HM801CTP-E	5	12.1	3.0 – 13.2	4.42	2.74	5.36	–
	GM1602AT8W-E	HM801CTP-E	6	14.0	3.0 – 16.0	4.43	3.12	6.30	A+
Wandgerät	GM1102AT8W-E	HM561KRTP-E	4	9.5	3.0 – 11.2	2.98	3.19	5.32	A
	GM1402AT8W-E	HM801KRTP-E	5	12.1	3.0 – 13.2	4.71	2.57	5.24	–
	GM1602AT8W-E	HM801KRTP-E	6	14.0	3.0 – 16.0	4.43	3.12	6.30	A+
Standgerät	GM1102AT8W-E	HM561FT-E	4	9.5	3.0 – 11.2	2.98	3.19	5.32	A
	GM1402AT8W-E	HM801FT-E	5	12.1	3.0 – 13.2	4.71	2.57	5.24	–
	GM1602AT8W-E	HM801FT-E	6	14.0	3.0 – 16.0	4.43	3.12	6.30	A+

## Twin Split Super Digital Inverter

	Aussengerät RAV-	Innengerät RAV-	HP	Leistung	Leistung	Leistungs-	EER	SEER	Energie-
				nominal	min. – max.	aufnahme			
				kW	kW	kW			
4-Wege- Kassettengerät	GP1101AT8-E	HM561UTP-E	4	10.0	2.6 – 12.0	2.32	4.31	7.06	A++
	GP1401AT8-E	HM801UTP-E	5	12.5	2.6 – 14.0	3.42	3.65	7.06	–
	GP1601AT8-E	HM801UTP-E	6	14.0	2.6 – 16.0	4.34	3.23	6.76	–
Kompaktes 4-Wege- Kassettengerät	GP801ATW-E	HM401MUT-E	3	7.1	1.9 – 8.0	1.73	4.10	7.8	A++
	GP1101AT8-E	HM561MUT-E	4	10.0	3.1 – 12.0	2.39	4.18	7.7	A++
	GP1101AT8-E	HM561MUT-E	4	10.0	2.6 – 12.0	2.60	3.84	6.16	A++
Kanalgerät	GP1101AT8-E	HM561BTP-E	4	10.0	2.6 – 12.0	2.58	3.87	5.86	A+
	GP1401AT8-E	HM801BTP-E	5	12.5	2.6 – 14.0	3.81	3.28	5.63	–
	GP1601AT8-E	HM801BTP-E	6	14.0	2.6 – 16.0	4.49	3.12	5.50	–
Flaches Kanalgerät	GP801ATW-E	HM401SDT-E	3	7.1	1.9 – 8.0	1.87	3.80	6.5	A++
	GP1101AT8-E	HM561SDT-E	4	10.0	2.6 – 12.0	2.73	3.66	5.60	A+
Deckengerät	GP801ATW-E	HM401CTP-E	3	7.1	1.9 – 8.0	1.60	4.44	7.82	A++
	GP1101AT8-E	HM561CTP-E	4	10.0	2.6 – 12.0	2.56	3.91	6.54	A++
	GP1401AT8-E	HM801CTP-E	5	12.5	2.6 – 14.0	3.68	3.40	6.17	–
	GP1601AT8-E	HM801CTP-E	6	14.0	2.6 – 16.0	4.60	3.04	5.89	–
Wandgerät	GP1101AT8-E	HM561KRTP-E	4	10.0	2.6 – 12.0	2.61	3.83	6.35	A++
	GP1401AT8-E	HM801KRTP-E	5	12.3	2.6 – 13.5	3.73	3.30	6.10	–
	GP1601AT8-E	HM801KRTP-E	6	14.0	2.6 – 16.0	4.65	3.01	5.88	–
Standgerät	GP1101AT8-E	HM561FT-E	4	10.0	2.6 – 12.0	2.61	3.83	6.35	A++
	GP1401AT8-E	HM801FT-E	5	12.3	2.6 – 13.5	3.73	3.30	6.10	–
	GP1601AT8-E	HM801FT-E	6	14.0	2.6 – 16.0	4.65	3.01	5.88	–